

K range contactors



Standard power ratings of 3-phase motors 50/60 Hz in category AC-3						Rated operational current in AC-3 up to 440V (A)	Rated operational current in AC-1 up to 440V (A)	Rated nonconductive voltage (V)	Instantaneous auxiliary contacts		Reference
220V 230V (kW)	380V 400V (kW)	415V (kW)	440V (kW)	500V (kW)	660V 690V (kW)						

Control circuit: a.c. ⌚											
1.5	2.2	2.2	3	3	3	6	20	690	1	-	GLC1-K0610
1.5	2.2	2.2	3	3	3	6	20	690	-	1	GLC1-K0601
2.2	4	4	4	4	4	9	20	690	1	-	GLC1-K0910
2.2	4	4	4	4	4	9	20	690	-	1	GLC1-K0901
3	5.5	5.5	4	4	4	12	20	690	1	-	GLC1-K1210
3	5.5	5.5	4	4	4	12	20	690	-	1	GLC1-K1201

Reversing contactors for motor control

Control circuit: a.c. ⌚											
1.5	2.2	2.2	3	3	3	6	20	690	1	-	GLC2-K0610
1.5	2.2	2.2	3	3	3	6	20	690	-	1	GLC2-K0601
2.2	4	4	4	4	4	9	20	690	1	-	GLC2-K0910
2.2	4	4	4	4	4	9	20	690	-	1	GLC2-K0901
3	5.5	5.5	4	4	4	12	20	690	1	-	GLC2-K1210
3	5.5	5.5	4	4	4	12	20	690	-	1	GLC2-K1201

Control circuit: d.c. ⎓											
1.5	2.2	2.2	3	3	3	6	20	690	1	-	GLP1-K0610
1.5	2.2	2.2	3	3	3	6	20	690	-	1	GLP1-K0601
2.2	4	4	4	4	4	9	20	690	1	-	GLP1-K0910
2.2	4	4	4	4	4	9	20	690	-	1	GLP1-K0901
3	5.5	5.5	4	4	4	12	20	690	1	-	GLP1-K1210
3	5.5	5.5	4	4	4	12	20	690	-	1	GLP1-K1201

Reversing contactors for motor control

Control circuit: d.c. ⎓											
1.5	2.2	2.2	3	3	3	6	20	690	1	-	GLP2-K0610
1.5	2.2	2.2	3	3	3	6	20	690	-	1	GLP2-K0601
2.2	4	4	4	4	4	9	20	690	1	-	GLP2-K0910
2.2	4	4	4	4	4	9	20	690	-	1	GLP2-K0901
3	5.5	5.5	4	4	4	12	20	690	1	-	GLP2-K1210
3	5.5	5.5	4	4	4	12	20	690	-	1	GLP2-K1201