


Features

- Center amplifying gate
- Metal case with ceramic insulator
- Low on-state and switching losses

Typical Applications

- AC controllers
- DC and AC motor control
- Controlled rectifiers

$I_{T(AV)}$	3500A
V_{DRM}/V_{RRM}	1900~3000V
I_{TSM}	44 KA
I^2t	9680 10 ³ A ² S



Symbol	Characteristic	Test Conditions	$T_j(^{\circ}C)$	Value			Unit
				Min	Type	Max	
$I_{T(AV)}$	Mean on-state current	180° half sine wave 50Hz Double side cooled $T_{hs}=64^{\circ}C$	125			3500	A
$I_{T(AV)}$	Mean on-state current	180° half sine wave 50Hz Double side cooled $T_{hs}=55^{\circ}C$	125			3835	A
V_{DRM} V_{RRM}	Repetitive peak off-state voltage Repetitive peak reverse voltage	V_{DRM} & V_{RRM} $t_p=10ms$ V_{DSM} & $V_{RSM}=V_{DRM}$ & $V_{RRM}+100V$	125	1900		3000	V
I_{DRM} I_{RRM}	Repetitive peak current	$V_{DM}=V_{DRM}$ $V_{RM}=V_{RRM}$	125			250	mA
I_{TSM}	Surge on-state current	10ms half sine wave	125			44	KA
I^2t	I^2t for fusing coordination	$V_R=0.6V_{RRM}$				9680	A ² s*10 ³
V_{TO}	Threshold voltage		125			0.99	V
r_T	On-state slop resistance					0.11	mΩ
V_{TM}	Peak on-state voltage	$I_{TM}=5000A, F=78KN$	25			2.40	V
dv/dt	Critical rate of rise of off-state voltage	$V_{DM}=0.67 V_{DRM}$	125			500	V/μs
di/dt	Critical rate of rise of on-state current	$V_{DM}=67\% V_{DRM}$ to 2000A, Gate pulse $t_r \leq 0.5\mu s$ $I_{GM}=1.5A$ Repetitive	125			250	A/μs
I_{rm}	Reverse recovery current	$I_{TM}=1500A, t_p=1000 \mu s,$ $di/dt=-20A/\mu s,$ $V_R=50V$	125			250	A
t_{rr}	Reverse recovery time					26	μs
Q_{rr}	Recovery charge					3250	μC
I_{GT}	Gate trigger current	$V_A=12V, I_A=1A$	25	40		300	mA
V_{GT}	Gate trigger voltage			0.8		3.0	V
I_H	Holding current			20		300	mA
V_{GD}	Non-trigger gate voltage	$V_{DM}=67\% V_{DRM}$	125	0.3			V
$R_{th(j-h)}$	Thermal resistance Junction to heatsink	At 180° sine double side cooled Clamping force 78KN				0.010	°C/W
F_m	Mounting force			70		85	KN
T_{stg}	Stored temperature			-40		140	°C
W_t	Weight				1100		g
Outline	KT84dT						




Fig.1




Fig.2




Fig.3




Fig.4




Fig.5




Fig.6




Fig.7




Fig.8




Fig.9




Fig.10

Outline:

